


LED converter 500 mA, 1-10V dimmable (analog)

Article no. 17824010

Light.
For Generations.



Tender
LED converter 500 mA, 1-10V dimmable (analog), , Rectangular.This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 0.75-1.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 500 mA, Voltage: 230V AC 50Hz , Power: 27 W, Dimmable: Yes, Control: 1-10 V.

Article data	
Article no.	17824010
GTIN	4251433924029
Short description	LED converter 500 mA, 1-10V dimmable (analog)
Material	Plastic
Shape	Rectangular
Length	146 mm
Width	43.5 mm
Hight	30 mm
Weight	0.141 kg
stamp	ENEC 05, EL
Conformance	CE

LED converter 500 mA, 1-10V dimmable (analog)

Article no. 17824010

Light.
For Generations.

Operating technology of driver	
AC nominal voltage min	198 V
AC nominal voltage max	264 V
Frequency min	50 Hz
Frequency max	60 Hz
DC nominal voltage min	176 V
DC nominal voltage max	275 V
Protection class	II
Degree of protection	IP20
Power min	5 W
Power max.	27 W
Output_ripple_current	3
Starting current	5A 50µs
Suitable for emergency lighting	No
measure point (tc)	85 °C
Version	without
Power factor	0.95
max. no. lights on B16 A	50
Output voltage max	54.00 V
Output voltage min	10.00 V
Flicker value Pst LM	1.00
Control	1-10 V
Number of poles	2
Environment temperature (ta)	-25 °C up to +40 °C
Measure point (tc)	max. +80 °C
Output current	500 mA

Packing data	
Gross weight	0.163 kg
Length of packaging	60 mm
Packaging width	30 mm
Packaging height	165 mm
Disposal at end of life	This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately. By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.